Quick Start Guide

MICROSENS

MS659150M

Dual Band 4x4 Wi-Fi 6 Indoor Access Point

LED Indicator



COLOR	STATUS	DESCRIPTION
0	OFF	Device is not receiving power
;•;	Flashing Amber	Device is being powered on
; or ; •;	Cyclic between Amber/Red	Firmware upgrading in process
•	Solid Red	Device is in serious error and cannot provide services normally
•	Solid Amber	Device has no Internet access
	Solid Green	Device serves as the Agent role
	Solid Blue	Device serves as the Controller role or Standalone



- Ceiling mount step 2 –
 attach ceiling mount hra
 - attach ceiling mount step 2 attach ceiling mount bracket to Ceiling T-Bar



Fig.2-1



 Ceiling mount step 3 – connect the ethernet with POE to the 2.5GE port or connect the DC12V and check LED indication for device boot up



 Ceiling mount step 4 – attach the device the ceiling mount bracket





Remove device from bracket

1 Step 1 – Lift the latch



Fig.1-1

2 Step 2 – Push the device out of bracket



Wall Mount Installation





D = 5mm L >= 30mm(with > 25mm inside wall) DK <= 10mm

Web UI sign-in

Customer can use Web UI to configure MS659150M. In order to login Web UI, please

- Open a web browser and enter the URL <u>https://ms659150m.local</u> in the address bar to access to the Access Point.
- Log in to the Web UI using the default username: admin and password (Located on bottom of your Access Point).

M Enterprise Access Point × +		
→ C ▲ Not secure ms659150m.local/1.00.33M	/login.html	
	MICROSENS	
	MS659150M	
	Username	
	Password 📀	